

ONLY PICKED UP PHASES RECLOSER CONTROL**FIELD OF THE INVENTION**

The present invention relates in general to the field of electrical power distribution systems. More particularly, the present invention relates to reclosers.

BACKGROUND OF THE INVENTION

A common problem in almost any electrical power distribution system is a momentary disruption of electrical service, such as might be caused by a momentary short circuit. For example, power lines strung between poles could swing under wind loading, momentary touching each other or a grounded conductor. Things may fall across exposed wires, arcing could occur, or other transitory events could cause momentary power line short circuits or current surges which could burn out a fuse or trip a circuit breaker. Most of these faults are self correcting and do not require permanent fuse or circuit breaker protection because they terminate quickly. If a fuse should burn out or a circuit breaker should trip, the power line would be open and customers

would be deprived of their electrical power. Service calls to replace fuses or reset circuit breakers would then be required, thus escalating the customer's costs.

A recloser is a fault-interrupting device used to sense current, voltage, and/or frequency and isolate faulted portions of distribution feeders. A recloser is operated by a recloser control
5 device, which can be an electronic control circuit. Reclosers are inserted into power lines to protect a power distribution system.

A recloser senses the peak value of the current conducted and interrupting its flow by opening or tripping a recloser before a fuse blows. After an interval, the recloser closes, thereby restoring power to the system where it remains closed until the next fault is sensed.

10 The rate at which a fuse will blow and interrupt current is a function of the thermal heating of the fusible element. The rate of thermal heating is proportional to the power generated by the fault and each fuse has a time current characteristic which describes the time interval required to interrupt the fault current. The time interval is generally approximately inversely
15 proportional to the value of the root mean square of the fault current. It is desirable to coordinate the recloser with the fuses to be saved to insure that the recloser in fact interrupts temporary fault currents before the fuses to be protected are blown. This is generally done by approximating the root mean square value of the fault current by sensing its peak value.

It must also be recognized that some faults which occur on a power distribution line are temporary, such as those caused by a branch momentarily falling against the line. Some faults
20 are of a more permanent nature such as those caused by a line falling to the ground. As a consequence, reclosers are programmed so that they will trip a limited number of times within a short duration before locking open.

At some magnitude of fault current it is desirable to have the recloser open immediately to protect the line rather than following a time current characteristic. At intermediate fault levels
25 it may be desirable from the power distribution standpoint to delay opening the recloser to allow the fault to clear itself or a fuse to operate. Many reclosers have alternate time current characteristics which achieve this goal. Typically a recloser will allow two shots or trip operations to follow a fast time current characteristic and two additional shots along a somewhat slower time current characteristic before locking open or out.

Conventional reclosers for three-phase systems open all three phases at the same time upon detection of a fault on any one phase. Other three-phase systems implement three single-phase reclosers, one on each phase. In these systems, each single-phase recloser is independently controlled. This is costly and does not allow for the phases to be responsive to one another.

5 Thus, in a typical configuration, for a fault, the recloser will open to clear the fault. Note that for any fault, e.g. single-phase-to-ground faults, phase-to-phase faults, phase-to-phase-ground faults, and three-phase faults, a typical recloser will open all three phases. For single-phase feeders, opening all three phases for single-phase fault results in more customers losing power than necessary. However, if an electric utility were to employ traditional single-phase protection
10 on their distribution system, it would be implemented with three single-phase mechanical reclosers - one for each phase. This provides per phase approach to single-phase faults but if there is an evolving fault, such as, for example, two or more phases are faulted, then the tripping and subsequent reclosing is also always done single-phase. Totally independent single-phase devices can also be involved in a race condition. For phase-to-phase faults, if one phase was to
15 operate more quickly than the other, the recloser may not correctly isolate the second faulted phase.

It is thus desirable to provide recloser control that can overcome the problems of the prior art. In this way, an electric utility can protect for single-phase, two-phase, and three-phase faults using the same recloser.

20 SUMMARY OF THE INVENTION

The present invention is directed to recloser operation that is responsive to the prevailing fault conditions. An only picked up phases (OPUP) technique trips a recloser for only the phases that are in a fault condition (i.e., one phase gets tripped for single-phase only fault conditions, two phases get tripped for two-phase fault conditions, and three-phases get tripped for three-phase
25 fault conditions.)

According to one embodiment within the scope of the present invention, a method for controlling a recloser for a three-phase electrical power line comprises monitoring the three

phases of the power line, determining which of the three phases have an associated fault, and opening the phases on the power line that have the associated fault.

According to aspects of the invention, determining which of the three phases have an associated fault comprises comparing a line current through each of the three phases to a predetermined current. A fault occurs on one of the phases when the line current on the associated phase exceeds the predetermined current.

According to further aspects of the invention, determining which of the three phases have an associated fault comprises detecting a fault in at least one of the three phases, starting a countdown timer associated with each faulted phase, and determining the faults still present after one of the associated countdown timers has expired.

According to further aspects of the invention, opening the phases on the power line that have the associated fault comprises opening only one phase if only one fault is determined, the only one phase being associated with the fault, opening only two phases if only two faults are determined, the only two phases being associated with the two faults, and opening all three phases if three faults are determined.

According to another embodiment within the scope of the invention, a recloser control system for a three-phase electrical power line comprises a recloser having three poles, each pole corresponding to an associated one of the three phases of the power line and being capable of opening or closing the associated phase of the power line, and a recloser controller coupled to the recloser for controlling the setting of the poles depending on the line current appearing in the phases on the power line. One pole opens the associated phase of the power line if the line current on only the associated phase exceeds an associated predetermined current, two poles open the two associated phases of the power line if the line current on each of only two associated phases exceeds an associated predetermined current, and all poles open all the associated phases of the power line if the line current on three phases exceeds the associated predetermined current.

According to aspects of the invention, the recloser controller comprises a countdown timer for determining whether a phase that has entered a pickup state should be tripped.

The foregoing and other aspects of the present invention will become apparent from the following detailed description of the invention when considered in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

5 Figure 1 is a simplified schematic diagram of a system in which the present invention may be embodied; and

 Figure 2 is a flow chart of an exemplary method of operation in accordance with the present invention.

DESCRIPTION OF EXEMPLARY EMBODIMENTS AND BEST MODE

10 The present invention is directed to systems and methods for controlling a recloser so that it trips on one phase for single-phase only fault conditions, or all phases for multi-phase fault conditions.

 A simplified schematic diagram of a system in which the present invention may be embodied is shown in Fig. 1. A recloser 10 is a switch that opens and closes a power line 5 (e.g.,
15 between a substation and a load), and which is operated by a recloser control device 20 such as an electronic control circuit. It should be understood that the term "recloser" covers various combinations of reclosers, sectionalizers, circuit breakers and the like, which may also be used within the scope of this invention. The power line 5 is a three-phase power line. The recloser 10 comprises three poles 15. Each pole 15 is connected to an associated wire on the power line 5,
20 thereby being energized by an associated phase. The recloser 10 could monitor system currents and voltages.

 The basic components of an automatic recloser 10 are a high-speed circuit breaker, overcurrent protection, trip logic, and automatic closing logic with an operation counter. When
25 an overcurrent of sufficient magnitude (i.e., greater than a predetermined amount of current) flows through the recloser 10, the tripping action is initiated and a circuit interrupting contact within the pole 15 opens with an operation counter advancing one count. After a preset time delay, the recloser contacts are automatically closed, thereby re-energizing the line 5. If the fault persists,

this tripping and reclosing sequence is repeated a predetermined number of times, as set by the controller 20, until a lockout function is initiated. If the fault was transient and cleared during any period when the recloser 10 was open, then the recloser 20 will remain closed after a short time delay reset to its original condition ready for the next operation.

- 5 An exemplary recloser for use with the present invention is the VR-3S recloser manufactured and distributed by ABB Power T&D Company, Inc., Raleigh, North Carolina. Magnetic actuators open and close the recloser's main contacts.

 The recloser 10 is controlled by microprocessor-based controller 20 that contains software. There are two basic design areas that make up a microprocessor-based controller 20. The physical
10 elements, such as integrated circuits, resistors, capacitors, displays, switches, and so forth, are called "hardware". Once constructed, they are not readily changeable. The second basic design area in the microcomputer includes computer programs and documentation. These elements are called "software" since they are readily changeable.

 A microcomputer based on a microprocessor and associated memories and interfacing
15 components is used in the recloser controller 20 to process input signals in a manner appropriate to the basic requirement for a recloser control. The microprocessor performs the various arithmetic and logic functions of the control. In particular, the required logic circuits as well as capabilities for servicing are typically included.

 A power supply is typically provided in a recloser control system and provides power to
20 other components of the control system and includes power storage means to supply power when the protected lines are interrupted. A secondary overcurrent trip circuit in the control functions independently of the microcomputer when the microcomputer is disabled to effect a trip operation of the recloser. A protective input network protects the controller's low power devices from the hostile environment of the power distribution system and scaling means are used to allow the
25 microcomputer and associated circuitry to function with more precision in the range of input signal magnitudes where precision is desirable and to allow the control to function with a limited number of components over a wide range of input signals.

 Memory is provided for temporarily and/or permanently storing data. In a recloser 10, for example, this information would include line current magnitudes. ROM is preferably

electrically programmable for easy modification and is used for storing programming information. In a recloser controller 20, for example, the memory module contains command information including multiple time-current characteristic curves.

The front panel of a recloser controller 20 may include a display for displaying information. A keyboard or other input device may be used for entering information. Indicator lamps provide status information such as recloser open, recloser closed, control lock out, above minimum trip, malfunction and lock in.

Through the use of the switches and keyboard mentioned above, the operations of the device can be controlled by command information. Typical command information for a recloser controller includes first time current characteristics for phase and ground currents which usually result in the more rapid tripping of the recloser 10, and second time current characteristics for phase and ground currents which usually result in the recloser 10 remaining closed longer under fault conditions. Other command information includes minimum trip levels for phase and ground currents which in a recloser controller begins the timing process in accordance with the time current characteristic, number of shots to lock out under phase and ground faults, and number of times which a given time current characteristic will be followed. Further command information may include a reset time interval which determines the duration which a counter recording the shot number will retain that information under non-fault conditions, and multiple reclose intervals which determine the time that the recloser 10 will remain open. Additional command information may include a high current constant time feature which allows the recloser 10 to remain closed only for a fixed duration under certain magnitudes of fault currents. Thus, if there is a fault, the line 5 is opened for a short period of time. At an end of a given time period following the opening of the line 5, the recloser 10 closes the line 5. If the abnormal condition persists, the recloser 10 again opens and closes the line 5.

It should be understood any of a number of microprocessors could be used to the same effect described above. Each manufacturer's family requires that the peculiarities of their devices be satisfied and in the microcomputer portion of the recloser controller 20, and it would be impossible to go into sufficient detail to describe the functioning control and be sufficiently general to adequately describe the use of alternative devices. One skilled in the art could readily

amplify and modify the description given to make them applicable to the devices of other manufacturers by reading the normal technical literature provided by the manufacturer of another device. Moreover, it would be extremely confusing to attempt to describe all the minor details contained within the software and only the more general software modules and programs are described since one skilled in the art could readily flesh out the skeleton provided.

An exemplary control unit is the PCD2000 power control device manufactured and distributed by ABB Power T&D Company, Inc., Raleigh, North Carolina. The control device can provide an interface for remote communication with SCADA systems using MODBUS RTU, MODBUS ASCII, and DNP 3.0 protocols. The controller can be programmed to implement other protocols. Ports are available for external links through a radio, modem, or direct fiber optic communications, for example.

In accordance with the invention, each single phase is individually monitored and can be tripped through the protection elements on the phase that detects fault current (i.e., current above the pickup threshold level) to initiate a pole 15 to trip open. In determining if a single phase is faulted, a protection element within the recloser detects a fault condition. The protection element enters pickup, then after predetermined time elapses, a trip operation results. It is possible to trip any and all phases that are in the pickup state at the time trip is determined. In the only picked up phases (OPUP) process according to the present invention, if a single-phase fault is detected or picked up on one pole, a single-phase trip will occur. If two phases are detected to have faults (via phase or neutral detection), then the two poles and associated phases will trip, and if three phases pickup or detect a fault, then the controller will direct all three poles to trip.

Figure 2 is a flow chart of an exemplary method of operation in accordance with the present invention. During power delivery, the recloser 10 monitors the three phases of the power line 5 (e.g., phases A, B, and C). If a fault is detected on phase A, at step 100, then a timer is started at step 110 by the controller and subsequently decremented at step 120. It is determined at step 130 if the timer has finished counting down. If not, then it is determined at step 140 if the fault is still present. If the fault is not present (i.e., it has cleared), then the timer is cleared (i.e., re-set) at step 145, and monitoring resumes. If the fault is still present at step 140, then the timer continues to decrement at step 120.

If the timer has finished its predetermined time count at step 130 with the fault still being present, then it is determined at step 150 if any of the other two phases are timing a fault. If so, then those phases having a fault (e.g., in pickup or timed out beyond pickup) are tripped at step 160; otherwise, only the faulted phase (here, phase A) is tripped at step 170.

- 5 Similarly, for phases B and C, if a fault is detected (at steps 200 and 300, respectively), an associated timer is started (210, 310) and subsequently decremented (220, 320). It is determined if the timer has completed its countdown (230, 330). If not, then it is determined if the fault is still present (240, 340). If the fault is not present (i.e., it has cleared), then the associated timer is cleared (245, 345), and monitoring resumes. However, if the fault is still
10 present, then the timer continues to decrement.

Similar to phase A, if the timer has finished its predetermined countdown with the fault still being present, then it is determined at step 150 if any of the other two phases are timing a fault. If so, then those phases having a fault (one, two, or three phases) are tripped at step 160; otherwise, only the faulted phase is tripped at step 170.

- 15 Thus, in accordance with the present invention, only those phases on the recloser that have a fault will be tripped. This is advantageous, if for example, a fault occurs only on phases A and B. In this case, only loads (customers) connected to phases A and B will experience an outage but the other phase (e.g., phase C) will not experience any interruption of power and will stay energized.

- 20 Moreover, each pole on the recloser is tripped (opened) independently if the controller detects a fault on only any one of the three phases. This is advantageous, if for example, a fault occurs only on phase A. In this case, only loads (customers) connected to phase A will experience an outage but the other two phases (e.g., phase B and phase C) will not experience any interruption of power and will stay energized.

- 25 The present invention provides a control capability function of the recloser to trip, reclose, and/or lockout whenever a fault is detected on one-phase independently, two-phases sequentially or three-phases simultaneously. This recloser control technique allows an electric utility to avoid unnecessary three-phase outages of their distribution network during an independent, single-phase, transient event, or a two-phase event. In this manner, all faulted phases are isolated.

Moreover, the present invention provides a level of protection, in that, if the independent single-phase transient fault were to evolve into another phase or phases, the recloser control method recognizes this condition and activates the recloser to those phases of the recloser that are affected (i.e., have a fault). The recloser control recognizes if there is more than one-phase involved (e.g., two-phases or three-phases evolving from the initially detected single-phase fault). Then the present invention initiates a two-phase or three-phase trip and subsequent reclose or lockout because the fault has evolved or is moving from one phase to another, thereby increasing the possibility of equipment damage.

The recloser control technique of the present invention allows an electric utility to prevent costly three-phase outages of their distribution network where catastrophic outages can be attributed to a single-phase transient type fault evolving into a significant two-phase and three-phase fault. The present invention improves the reliability of the electrical power system (e.g., during catastrophic events such as hurricanes, tornadoes, thunderstorms, and earthquakes), thereby minimizing the electrical and mechanical damage to feeder equipment, and thus saving the electric utility time, money, and resources.

In accordance with the present invention, all phases shall operate together rather than with momentary delay from phase-to-phase that may otherwise occur as a result slight timing differences of individual devices.

Thus, the present invention allows all phases to act at the same time, and trips one phase, two phases, or three phases based on fault type. It is contemplated that both tripping and lockout can be implemented on single-phase or two-phase.

For single-phase tripping, two-thirds of outages on line-ground faults are prevented. For example, the controller trips on A phase only, with lockout on that phase only. For two-phase tripping, one-third of outages on line-ground faults are prevented. For example, the controller trips on A and B phases only, with lockout on those phases only. The invention provides better system reliability and continuity of service.

The invention may be embodied in the form of appropriate computer software, or in the form of appropriate hardware or a combination of appropriate hardware and software without departing from the spirit and scope of the present invention. Further details regarding such

hardware and/or software should be apparent to the relevant general public. Accordingly, further descriptions of such hardware and/or software herein are not believed to be necessary.

Although illustrated and described herein with reference to certain specific embodiments, the present invention is nevertheless not intended to be limited to the details shown. Rather,
5 various modifications may be made in the details within the scope and range of equivalents of the claims and without departing from the invention.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199